



C1.5

GENERATOR SET

RATINGS AND FUEL CONSUMPTION

Generator Set

	ekW @ .8pf	kVA	rpm	U.S. g/h	g/bkW-hr	EPA - IMO - EU
60 Hertz	13.0	16.5	1800	1.2	268.2	T3C - NST - IW
50 Hertz	11.0	13.5	1500	1.0	264.1	T3C - NST - IW

Generator Set – Single Phase

	ekW @ 1.0pf	kVA	rpm	U.S. g/h	g/bkW-hr	EPA - IMO - EU
60 Hertz	12.0	12.0	1800	1.2	290.5	T3C - NST - IW
50 Hertz	10.0	10.0	1500	1.0	290.5	T3C - NST - IW

	L	H	WE
Open Set	41.9 in/1065 mm	28.7 in/733 mm	19.8 in/504 mm
Enclosed Set	46 in/1170 mm	30.8 in/783 mm	24 in/608 mm

In-line 3, 4-Stroke-Cycle Diesel

Aspiration	NA	
Bore x Stroke	3.31 x 3.5 in	84 x 90 mm
Displacement	91 cu in	1.5 liter
Rotation (from flywheel end)	Counterclockwise	
Generator set weight (approx)	703/908 lb	319/412 kg